

THE WORLD'S SPEED IS OUR BEAT



## MILMEGA 'AS' Series Solid State Amplifier Range

## Model: AS0827-400 Broad Band Amplifier




- Calibrated Dual Directional Coupler fitted as standard
- Ethernet, USB and RS232 or GPIB and RS232 included in price
- Unique 5 year parts and labour warranty on all MILMEGA amplifiers.

The AS0827 series of solid state power amplifiers follows the MILMEGA tradition for compact, upgradeable microwave power amplifier solutions with field proven reliability.

METEK

Developed to cover the frequency band 0.8-2.7GHz in a single band this amplifier combines a compact design with market leading performance.

The unit is air-cool with integral fans, and is protected against faulty cooling by excess temperature sensing. A safety interlock connector is provided, which the user can short circuit to ground, to put the amplifier into standby mode. Front panel indicators are provided to indicate over-temperature and RF interlock condition



## **Amplifier Specification**

| Frequency Range                 | 0.8 to 2.7 GHz                    |
|---------------------------------|-----------------------------------|
| Psat (min)                      | 447W                              |
| P1dB (min)                      | 400W                              |
| Gain (min)                      | 52dB                              |
| Gain (nominal)                  | 58dB                              |
| Gain Variation (max)            | +/- 2.0dB                         |
| Harmonics at P1dB               | -20 dBc                           |
| Third order intercept point IP3 | 10dB > P1dB                       |
| Noise figure                    | 6.0dB                             |
| Input Power (no damage)         | +15 dBm                           |
| Output VSWR tolerance           | Infinite any phase                |
| Stability                       | Unconditional                     |
| Output impedance                | 50 Ohm                            |
| Output VSWR                     | 2:1 (typical)                     |
| Input VSWR                      | 2.3:1 (max)                       |
| Spurious                        | -70 dBc (min) -80 dBc (typical)   |
| Safety interlock                | Via rear panel mounted BR2-female |
| Supply Voltage - 1 Phase        | 90 to 132 or 180 to 240 Vac       |
| Supply Frequency                | 47 to 60 Hz                       |
| Supply Power                    | 5 kVA (typical full power)        |
| RF Input                        | Type N female                     |
| RF Output                       | Type 7/16 female                  |
| Dimension                       | 19 inch, 20U case, 780mm Deep     |
| Weight                          | 165 kg                            |

Amplifiers that meet today's and tomorrow's needs through upgradability.



Specifications subject to change without notice. MILMEGA is an ISO accredited Company. Products are designed and manufactured under strict quality and environmental requirements of ISO goo1.



**RF/Microwave Amplifiers** 

MILMEGA Limited Park Road, Ryde, Isle of Wight PO33 2BE United Kingdom Tel. +44 (0) 1983 618004 Fax. +44 (0) 1983 811521 sales@milmega.co.uk www.milmega.co.uk